



**Sealed Maintenance Free
GENSET Starting Unit**



The Battery


The Pure Lead-Tin VRLA battery has an unmatched peak power performance due to its thin plate design. This is a sealed maintenance free battery with no topping up required for life.

The Charger

The sophisticated SMPS battery charger with in-built protections ensures optimum charging of the batteries always. The periodic running of the genset for charging of the batteries is eliminated.

Features and Benefits

- ▶ **Maintenance Free** : No Topping up or Specific Gravity Checks
- ▶ **Ready-to-use** : Filled and Factory Charged
- ▶ **Reliability** : In-built Charger ensures that Battery is always Fully Charged
- ▶ **Cost Advantage** : Low Cost of Ownership over its Long Life Time
- ▶ **Xcell** : Integrated Battery + Charger System



Recommended circuit diagram
(Battery will be fully charged if charger is connected to AC mains at all times)

Xcell Model Dimensions & Selection Chart

Pure Lead Power Pack Model*	Dimensions in mm			Genset Rating KVA	Weight (Apprx) In kgs**
	L	W	H		
XCL 12V 2000	355	175	182	15, 20, 25	12.5
XCL 12V 3200	355	175	235	30, 40, 50, 62.5, 82.5, 100, 125	16.5
XCL 24V 2000	430	255	182	50, 62.5, 70, 100, 110, 125, 140	23
XCL 24V 3200	430	255	235	160 to 500	31.0
XCL 24V 8000	600	450	290	590, 625, 750	76.0
XCL 24V 10000	600	450	320	1000 to 1500	93.0

* The suffix 2000 & 3200 represent 20Ah and 32Ah respectively at C₂₀

**Battery + Charger + Protective Steel Enclosure

- Selection depends on starting voltage (12 V / 24 V). Power Pack models selected for the given Genset KVA ratings are based on ambient temperature of 27 deg. C.

- In accordance with its policy of continuous improvement the company reserves the right to change specifications and designs without notice. Illustrations, data, dimensions and weights given in this brochure are for guidance only and cannot be held binding on the company.

Delhi	T: +91 124 4783 333 / 4783 322	F: +91 124 4783 300	E: delhi@hbl.in
Mumbai	T: +91 22 3912 0301 - 307	F: +91 22 2789 3498	E: mumbai@hbl.in
Chennai	T: +91 44 4297 0300 to 309	F: +91 44 4297 0333	E: chennai@hbl.in
Kolkata	T: +91 33 2486 3967 / 2486 3985	F: +91 33 2486 3967	E: calcutta@hbl.in
Bangalore	T: +91 80 4113 0303 - 05	F: +91-80-4113 0306	E: bangalore@hbl.in
Hyderabad	T: +91 40 2779 1641 / 5434	F: +91 40 2779 5419	E: hro@hbl.in
Kochi	T: +91 484 305 2454 / 74	F: +91 484 309 4636	E: csgkochi@hbl.in
Ahmedabad	T: +91 079 2646 3522	F: +91 079 2646 3522	E: ahmedabad@hbl.in



HBL Power Systems Ltd.

8-2-601, Road No. 10, Banjara Hills, Hyderabad - 500 034, A.P, India. Tel : +91-40-23355575 / 23355085 Fax : +91-40-23355048

Website : www.hbl.in, E-mail : xcell@hbl.in